

## Rozładowanie stałym prądem

typ	1.94V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	45.6	32.2	19.9	11.0	7.7	6.0	5.0	3.3	2.7	1.5
M12V50FT	67.4	43.7	26.1	14.8	10.5	8.2	6.7	4.4	3.6	1.9
M12V60FT	73.0	49.7	30.6	17.6	12.7	10.1	8.5	5.6	4.6	2.5
M12V90FT	106.8	76.0	47.1	26.8	19.5	15.5	12.7	8.4	6.9	3.7
M12V105FT	121.9	79.9	52.4	30.6	22.4	17.9	14.9	9.7	8.0	4.2
M12V125FT	97.5	77.9	62.2	36.7	27.0	21.2	17.4	11.5	9.5	5.0
M12V155FT	122.3	95.1	74.0	46.3	33.5	26.4	21.9	14.4	11.8	6.3
M06V200FT	131.7	131.7	90.7	55.0	40.4	32.4	27.4	18.8	15.4	8.3

typ	1.92V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	50.2	34.4	21.4	11.8	8.3	6.4	5.3	3.5	2.9	1.6
M12V50FT	73.0	46.8	28.0	16.0	11.2	8.7	7.1	4.7	3.8	2.1
M12V60FT	79.2	53.7	33.1	18.9	13.6	10.8	9.1	6.0	4.9	2.6
M12V90FT	120.0	81.2	50.5	28.6	20.5	16.2	13.5	8.9	7.3	3.9
M12V105FT	132.4	86.0	55.9	32.4	23.5	18.8	15.8	10.3	8.4	4.5
M12V125FT	125.0	91.7	67.3	39.7	29.2	22.7	18.6	12.2	10.1	5.4
M12V155FT	149.9	108.7	78.8	49.1	35.1	27.7	23.0	15.4	12.5	6.6
M06V200FT	159.9	155.7	97.8	59.0	43.1	34.5	29.0	20.0	16.4	8.8

typ	1.90V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	56.4	36.8	22.9	12.5	8.8	6.8	5.6	3.7	3.1	1.7
M12V50FT	79.2	50.2	29.6	17.0	11.9	9.2	7.5	4.9	4.0	2.2
M12V60FT	86.6	58.0	35.7	20.2	14.5	11.5	9.6	6.4	5.2	2.8
M12V90FT	130.0	86.7	54.0	30.3	21.7	17.2	14.2	9.3	7.7	4.1
M12V105FT	141.4	91.7	59.4	34.1	24.7	19.6	16.4	10.9	8.9	4.7
M12V125FT	152.6	105.3	72.6	42.4	31.1	24.0	19.7	12.9	10.6	5.7
M12V155FT	177.4	122.0	83.9	52.0	37.0	29.1	24.2	16.4	13.3	7.0
M06V200FT	188.0	166.8	105.2	63.1	45.8	36.6	30.7	21.1	17.3	9.3

typ	1.87V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	61.3	39.3	24.4	13.3	9.3	7.2	5.9	3.9	3.2	1.7
M12V50FT	85.7	53.8	31.2	17.6	12.5	9.7	7.9	5.2	4.3	2.3
M12V60FT	93.3	60.9	37.4	21.2	15.2	12.0	10.0	6.7	5.5	2.9
M12V90FT	142.0	93.2	57.4	32.1	23.2	18.0	14.8	9.8	8.0	4.4
M12V105FT	153.1	97.9	62.6	35.8	25.8	20.5	17.1	11.5	9.3	4.9
M12V125FT	169.8	115.1	78.0	45.0	33.0	25.5	20.9	13.7	11.2	6.1
M12V155FT	196.9	136.6	89.5	54.9	39.0	30.6	25.4	17.1	13.9	7.3
M06V200FT	231.5	182.7	115.8	67.0	48.6	38.7	32.5	22.4	18.3	9.8

typ	1.85V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	64.8	41.0	25.4	13.8	9.6	7.5	6.1	4.0	3.3	1.8
M12V50FT	90.2	56.3	32.2	18.3	13.0	10.0	8.2	5.4	4.4	2.4
M12V60FT	98.4	63.0	38.6	21.9	15.7	12.4	10.3	6.9	5.6	3.0
M12V90FT	152.0	97.9	59.5	33.2	23.6	18.4	15.1	10.1	8.3	4.5
M12V105FT	155.0	102.0	64.7	36.9	26.6	21.0	17.6	11.8	9.6	5.2
M12V125FT	175.0	119.2	79.2	46.5	34.3	26.5	21.6	14.1	11.6	6.3
M12V155FT	220.5	150.4	92.9	56.9	40.4	31.6	26.2	17.6	14.3	7.6
M06V200FT	259.7	191.6	122.4	70.1	50.6	40.2	33.6	23.0	18.9	10.1

typ	1.83V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	66.9	41.9	25.8	14.0	9.8	7.6	6.2	4.1	3.4	1.8
M12V50FT	93.0	57.9	32.7	18.4	13.1	10.3	8.4	5.5	4.5	2.4
M12V60FT	101.7	65.0	39.3	22.3	16.0	12.6	10.5	7.0	5.7	3.0
M12V90FT	159.1	100.8	61.0	34.0	24.0	18.7	15.4	10.2	8.4	4.6
M12V105FT	163.1	104.7	66.4	37.8	27.2	21.5	17.9	12.0	9.8	5.2
M12V125FT	186.9	124.6	81.8	47.7	35.2	27.1	22.2	14.5	11.8	6.3
M12V155FT	233.8	157.4	95.9	58.1	41.3	32.3	26.8	18.0	14.6	7.7
M06V200FT	276.5	199.5	126.2	71.9	51.8	41.0	34.2	23.4	19.3	10.2

typ	1.80V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	70.3	43.3	26.3	14.3	10.0	7.8	6.4	4.2	3.5	1.9
M12V50FT	97.3	60.1	33.5	18.7	13.3	10.1	8.6	5.7	4.7	2.4
M12V60FT	106.7	67.4	39.6	22.6	16.3	12.9	10.8	7.2	5.9	3.1
M12V90FT	170.0	105.2	63.0	35.0	24.6	19.1	15.7	10.4	8.6	4.7
M12V105FT	179.5	109.5	68.3	38.8	27.8	22.0	18.3	12.3	10.0	5.3
M12V125FT	204.4	132.2	85.1	49.3	36.3	27.9	22.8	14.9	12.1	6.4
M12V155FT	254.1	167.3	99.8	59.6	42.3	33.1	27.4	18.4	15.0	7.9
M06V200FT	297.5	210.7	132.7	75.1	53.8	42.5	35.4	24.1	20.0	10.5

typ	1.78V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	71.4	43.6	26.4	14.4	10.1	7.8	6.4	4.2	3.5	1.9
M12V50FT	98.3	60.7	33.8	18.9	13.4	10.5	8.7	5.7	4.7	2.4
M12V60FT	107.9	67.9	39.7	22.7	16.4	13.0	10.9	7.3	5.9	3.1
M12V90FT	174.0	106.8	63.6	35.2	24.7	19.2	15.8	10.5	8.6	4.7
M12V105FT	184.2	112.3	69.3	39.3	28.2	22.3	18.5	12.5	10.1	5.3
M12V125FT	214.0	136.3	86.7	49.9	36.8	28.3	23.1	15.1	12.3	6.5
M12V155FT	265.7	172.0	101.8	60.4	42.8	33.6	27.8	18.6	15.2	7.9
M06V200FT	309.2	216.3	134.3	76.3	54.6	43.0	35.8	24.3	20.0	10.6

typ	1.75V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	72.6	44.0	26.5	14.4	10.2	7.9	6.6	4.3	3.5	1.9
M12V50FT	99.3	61.0	34.3	19.1	13.5	10.6	8.8	5.8	4.7	2.5
M12V60FT	109.6	68.8	40.1	23.0	16.6	13.1	11.0	7.3	6.0	3.2
M12V90FT	178.0	108.0	64.0	35.5	24.9	19.4	15.9	10.6	8.7	4.7
M12V105FT	190.7	115.4	70.0	39.8	28.5	22.5	18.7	12.7	10.3	5.4
M12V125FT	233.6	141.7	88.1	50.5	37.2	28.6	23.4	15.2	12.4	6.5
M12V155FT	275.0	174.9	103.2	60.8	43.2	33.9	28.1	18.9	15.4	8.0
M06V200FT	323.4	220.5	135.2	76.9	55.2	43.6	36.3	24.6	20.2	10.7

typ	1.73V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	73.2	44.4	26.6	14.4	10.2	8.0	6.6	4.3	3.5	1.9
M12V50FT	100.2	61.3	34.4	19.1	13.6	10.7	8.9	5.8	4.7	2.5
M12V60FT	110.1	69.0	40.3	23.0	16.6	13.2	11.0	7.4	6.0	3.2
M12V90FT	184.0	109.2	64.4	35.6	25.0	19.4	16.0	10.6	8.7	4.7
M12V105FT	192.7	116.7	70.6	40.0	28.7	22.6	18.8	12.7	10.3	5.4
M12V125FT	236.4	143.8	88.8	50.8	37.3	28.8	23.5	15.3	12.5	6.7
M12V155FT	287.9	177.1	104.0	61.2	43.5	34.1	28.2	19.0	15.4	8.0
M06V200FT	333.3	223.4	136.2	77.4	55.5	43.9	36.5	24.7	20.3	10.7

typ	1.70V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	74.0	44.6	26.7	14.4	10.3	8.1	6.7	4.4	3.6	1.9
M12V50FT	101.5	61.5	34.6	19.3	13.7	10.7	8.9	5.8	4.7	2.5
M12V60FT	110.5	69.6	40.5	23.2	16.7	13.3	11.1	7.4	6.0	3.2
M12V90FT	187.9	110.4	64.7	35.8	25.1	19.5	16.0	10.6	8.7	4.8
M12V105FT	195.9	118.4	71.3	40.4	28.9	22.8	18.9	12.8	10.4	5.4
M12V125FT	241.6	147.1	89.7	51.3	37.5	29.0	23.7	15.5	12.6	6.7
M12V155FT	300.6	179.0	105.1	61.7	43.9	34.4	28.4	19.1	15.5	8.0
M06V200FT	343.0	226.4	137.2	77.8	55.8	44.1	36.7	24.9	20.4	10.8

typ	1.67V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	74.9	44.9	26.9	14.5	10.3	8.1	6.7	4.4	3.6	1.9
M12V50FT	102.9	61.7	34.7	19.3	13.8	10.8	9.0	5.9	4.8	2.5
M12V60FT	111.2	69.9	40.7	23.3	16.8	13.3	11.1	7.5	6.1	3.2
M12V90FT	191.1	111.5	64.9	35.9	25.2	19.6	16.1	10.7	8.8	4.8
M12V105FT	199.4	120.0	72.0	40.8	29.1	22.9	19.0	12.9	10.4	5.4
M12V125FT	248.1	150.5	90.6	51.7	37.6	29.2	23.9	15.6	12.7	6.8
M12V155FT	307.4	180.8	106.1	62.2	44.2	34.6	28.6	19.2	15.6	8.0
M06V200FT	351.8	229.3	138.3	78.3	56.1	44.3	36.9	25.1	20.5	10.8

typ	1.65V/ogniwo przy 20°C - rozładowanie w [A]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	20h
M12V35FT	75.5	45.0	27.0	14.6	10.3	8.1	6.8	4.4	3.6	1.9
M12V50FT	103.9	62.0	34.9	19.3	13.8	10.9	9.1	5.9	4.8	2.5
M12V60FT	111.4	70.5	70.5	23.4	16.9	13.4	11.2	7.5	6.1	3.2
M12V90FT	193.4	112.3	65.1	36.0	25.2	19.6	16.1	10.7	8.8	4.8
M12V105FT	200.4	120.7	72.7	41.0	29.2	23.0	19.1	12.9	10.5	5.4
M12V125FT	250.8	152.8	91.3	52.0	37.7	29.3	24.1	15.7	12.8	6.8
M12V155FT	312.0	182.6	106.9	62.5	44.4	34.7	28.7	19.2	15.6	8.2
M06V200FT	357.1	231.3	139.3	78.7	56.3	44.4	37.0	25.1	20.6	10.8

## Rozładowanie stałą mocą

typ	1.94V/ogniwo przy 20°C - rozładowanie w [W/blok]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	
M12V35FT	564.8	377.1	231.7	130.8	92.5	72.4	59.8	40.0	33.1	
M12V50FT	731.2	492.3	311.6	184.2	129.1	100.3	82.5	54.7	44.9	
M12V60FT	882.4	597.5	365.5	211.1	153.1	121.9	102.1	67.6	55.1	
M12V90FT	1184.4	889.4	562.1	324.3	235.1	187.1	156.7	103.6	84.5	
M12V105FT	1250.6	968.2	612.4	352.7	255.3	203.1	170.8	112.2	91.9	
M12V125FT	1159.7	1159.7	729.5	427.5	312.7	250.5	210.9	146.3	118.5	
M12V155FT	1337.5	1309.6	862.6	530.3	385.2	307.0	257.4	174.7	142.8	
M06V200FT	867.0	804.6	551.4	341.4	246.9	196.2	164.1	112.8	92.1	

typ	1.92V/ogniwo przy 20°C - rozładowanie w [W/blok]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	
M12V35FT	601.4	399.5	247.0	139.2	98.3	76.8	63.5	42.4	35.0	
M12V50FT	798.7	525.9	331.4	196.2	137.2	106.4	87.4	57.7	47.4	
M12V60FT	1017.8	644.8	392.9	224.7	162.1	128.6	107.4	71.9	58.5	
M12V90FT	1429.8	944.6	596.1	342.0	247.1	196.2	164.0	109.2	89.0	
M12V105FT	1526.2	1025.5	651.3	373.0	269.3	213.7	180.0	118.6	97.1	
M12V125FT	1237.5	1237.3	778.6	453.7	330.7	264.3	222.1	155.5	125.8	
M12V155FT	1627.0	1407.3	916.5	556.5	404.0	321.9	269.9	185.0	150.9	
M06V200FT	1011.9	857.1	585.0	363.9	262.2	207.9	173.4	118.8	96.9	

typ	1.90V/ogniwo przy 20°C - rozładowanie w [W/blok]									
	15'	30'	1h	2h	3h	4h	5h	8h	10h	
M12V35FT	641.1	422.3	262.3	147.5	104.1	81.3	67.1	44.8	37.0	
M12V50FT	868.5	561.2	351.7	208.2	145.3	112.5	92.3	60.8	49.9	
M12V60FT	1114.9	694.2	420.7	238.6	171.3	135.4	112.8	76.1	62.0	
M12V90FT	1546.2	1002.8	630.2	359.7	259.1	205.3	171.4	114.8	93.4	
M12V105FT	1642.2	1085.3	690.3	393.5	283.2	224.3	187.2	125.1	102.3	
M12V125FT	1321.4	1321.3	828.2	479.8	348.7	278.0	233.2	164.6	133.1	
M12V155FT	1916.5	1517.7	975.6	579.0	419.4	335.6	282.3	195.3	159.1	
M06V200FT	1153.5	921.0	620.7	386.1	277.5	219.6	183.0	125.4	102.3	

ETC Plus S.A.  
 ul. Drukarska 14  
 27-400 Ostrowiec Św.  
 tel.: 41 26 36 811  
 fax: 41 26 54 443

typ	1.87V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	679.4	444.8	278.0	155.8	109.7	85.5	70.5	47.0	38.7
M12V50FT	939.6	596.5	371.3	214.6	152.8	118.2	96.8	63.6	52.1
M12V60FT	1130.0	740.1	444.6	251.6	180.4	142.4	118.6	79.8	65.0
M12V90FT	1665.6	1061.7	665.7	377.7	271.1	214.3	178.5	120.0	97.6
M12V105FT	1771.9	1144.1	722.2	410.8	295.3	233.7	194.9	130.7	106.8
M12V125FT	1400.2	1400.2	873.7	504.7	366.2	291.6	244.4	168.5	139.8
M12V155FT	2350.7	1634.7	1042.1	605.5	440.8	351.8	295.4	203.1	165.5
M06V200FT	1340.7	1006.8	664.2	411.9	294.6	232.2	193.2	131.1	108.0

typ	1.85V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	710.7	460.1	288.5	161.3	113.5	88.4	72.8	48.4	39.9
M12V50FT	988.2	620.8	387.8	217.9	155.5	122.4	101.0	66.0	53.7
M12V60FT	1174.3	786.5	449.9	257.3	185.6	147.2	123.0	82.3	67.0
M12V90FT	1727.7	1098.2	689.6	389.8	279.2	220.3	183.3	123.4	100.4
M12V105FT	1782.8	1185.6	743.4	422.3	303.4	239.9	200.0	134.4	109.8
M12V125FT	2114.6	1454.2	905.2	521.3	377.5	300.3	251.4	172.9	144.2
M12V155FT	2466.3	1718.0	1083.1	626.5	454.8	362.4	303.8	209.4	170.4
M06V200FT	1475.7	1067.7	692.1	427.5	305.1	240.0	199.2	134.7	111.3

typ	1.83V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	730.7	468.5	293.0	163.8	115.1	89.7	73.9	49.1	40.5
M12V50FT	1014.9	633.9	396.3	221.4	157.6	123.8	102.6	67.3	54.5
M12V60FT	1217.5	804.6	458.9	261.7	188.5	149.3	124.6	83.6	68.0
M12V90FT	1794.9	1125.3	700.7	395.3	282.8	223.0	185.4	124.9	101.6
M12V105FT	1863.3	1216.9	760.4	431.2	309.5	244.5	203.7	137.8	112.3
M12V125FT	2178.1	1489.2	924.1	532.4	385.6	306.8	256.9	176.7	148.4
M12V155FT	2588.8	1776.4	1112.3	641.3	464.7	369.7	309.7	213.5	173.7
M06V200FT	1536.3	1110.3	712.8	437.1	311.4	244.8	203.1	138.0	112.8

typ	1.80V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	762.2	481.3	299.7	167.4	117.7	91.6	75.5	50.2	41.3
M12V50FT	1055.3	653.9	407.7	227.1	161.2	126.5	104.8	68.8	55.6
M12V60FT	1287.7	832.0	472.5	268.4	192.7	152.4	127.0	85.6	69.5
M12V90FT	1900.7	1167.8	717.5	403.5	288.2	227.0	188.6	127.0	103.4
M12V105FT	1983.5	1249.3	780.2	441.3	316.2	249.6	207.8	140.8	114.7
M12V125FT	2255.3	1532.4	949.6	545.4	394.3	313.3	262.1	180.0	151.8
M12V155FT	2772.8	1853.5	1148.0	658.7	476.0	378.0	316.1	218.0	177.3
M06V200FT	1649.4	1182.6	749.4	453.9	322.8	253.2	210.0	142.8	116.1

typ	1.78V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	773.6	485.1	301.5	168.5	118.5	92.3	76.0	50.5	41.6
M12V50FT	1059.0	658.2	409.8	228.2	162.0	127.1	105.3	69.1	55.8
M12V60FT	1315.2	840.1	476.4	270.2	193.9	153.2	127.7	86.1	69.9
M12V90FT	1940.9	1183.6	722.0	404.4	290.1	228.4	189.8	128.0	104.1
M12V105FT	2037.6	1272.8	789.6	446.4	319.8	252.4	210.1	142.4	115.9
M12V125FT	2291.4	1552.3	960.9	551.6	398.7	316.7	264.9	181.8	153.7
M12V155FT	2874.3	1892.8	1166.2	668.2	482.5	382.9	320.1	220.3	179.2
M06V200FT	1705.5	1212.0	760.2	457.8	325.2	255.3	211.5	143.7	117.0

typ	1.75V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	790.3	485.2	304.2	170.1	119.7	93.2	76.8	51.1	42.1
M12V50FT	1088.4	668.8	413.0	229.9	163.2	128.0	106.0	69.6	56.1
M12V60FT	1358.6	852.4	482.3	272.9	195.6	154.5	128.6	86.8	70.5
M12V90FT	1980.0	1200.0	728.7	405.0	290.7	229.8	190.8	129.5	105.3
M12V105FT	2116.1	1292.9	796.8	450.7	322.7	254.6	211.9	143.8	117.0
M12V125FT	2307.8	1562.8	966.7	553.4	399.6	319.3	267.0	183.1	155.3
M12V155FT	3014.4	1910.6	1171.8	673.9	484.9	386.4	322.9	220.8	180.1
M06V200FT	1798.2	1246.5	773.1	462.9	327.9	257.4	213.3	144.9	118.2

typ	1.73V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	794.8	487.2	305.9	170.9	120.2	93.6	77.1	51.2	42.2
M12V50FT	1094.7	671.1	413.7	230.5	163.7	128.4	106.4	69.8	56.3
M12V60FT	1371.5	855.0	483.7	273.7	196.1	154.8	128.9	87.0	70.7
M12V90FT	2016.2	1212.0	732.0	405.6	291.3	230.4	191.4	129.6	105.4
M12V105FT	2126.8	1304.7	800.1	451.9	323.5	255.3	212.4	144.1	117.2
M12V125FT	2324.2	1573.7	970.5	554.9	400.1	320.0	267.5	183.5	155.5
M12V155FT	3062.5	1928.2	1177.6	679.2	488.5	388.8	325.0	221.2	180.3
M06V200FT	1839.3	1281.3	782.1	465.3	329.4	258.9	214.2	145.2	118.5

typ	1.70V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	801.5	490.2	308.4	172.1	120.9	94.1	77.5	51.5	42.4
M12V50FT	1104.3	674.6	414.9	231.3	164.4	129.0	106.9	70.2	56.5
M12V60FT	1391.4	858.9	485.8	274.7	196.8	155.4	129.3	87.4	70.9
M12V90FT	2038.6	1221.0	735.0	406.3	292.1	231.0	192.0	129.8	105.6
M12V105FT	2143.0	1312.9	803.5	453.7	324.8	256.2	213.1	144.6	117.6
M12V125FT	2340.0	1582.4	974.0	555.8	400.7	320.3	268.2	185.4	155.8
M12V155FT	3137.2	1945.7	1183.5	682.7	492.0	390.4	326.4	222.1	180.9
M06V200FT	1906.5	1309.2	790.8	467.4	330.9	259.5	215.1	145.5	118.8

typ	1.67V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	808.2	493.2	309.2	173.3	121.7	94.7	77.9	51.7	42.6
M12V50FT	1113.9	678.1	416.1	232.2	165.0	129.5	107.4	70.5	56.7
M12V60FT	1412.1	862.9	487.7	275.7	197.0	156.1	130.3	87.7	71.2
M12V90FT	2061.3	1228.2	737.4	407.5	292.7	231.4	192.6	130.0	105.7
M12V105FT	2158.8	1321.2	807.0	455.5	326.0	257.1	213.9	145.1	118.0
M12V125FT	2357.6	1591.2	978.1	557.2	401.3	320.6	269.0	185.8	156.1
M12V155FT	3218.8	1961.7	1189.3	686.0	494.8	392.4	327.8	222.9	181.6
M06V200FT	1986.6	1339.2	799.8	469.5	331.8	260.1	215.4	145.8	119.4

typ	1.65V/ogniwo przy 20°C - rozładowanie w [W/blok]								
	15'	30'	1h	2h	3h	4h	5h	8h	10h
M12V35FT	812.8	495.3	309.9	174.1	122.2	95.0	78.2	51.9	42.7
M12V50FT	1120.4	680.5	416.3	232.7	165.5	129.9	107.7	70.7	56.9
M12V60FT	1424.8	865.8	489.6	276.6	197.5	156.4	130.6	87.9	71.3
M12V90FT	2073.8	1235.4	739.8	408.3	293.1	231.7	193.1	130.1	105.8
M12V105FT	2169.6	1326.8	809.4	456.7	326.8	257.7	214.4	145.4	118.2
M12V125FT	2373.6	1600.0	981.6	557.8	403.1	321.3	269.5	186.2	157.4
M12V155FT	3267.8	1977.3	1196.5	688.2	496.3	393.6	328.8	223.5	182.0
M06V200FT	2037.6	1354.8	805.5	471.6	332.7	260.7	216.0	146.4	119.7