

Tabele rozładowań

Rozładowanie stałym prądem

OPzS

1.90V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	81,5	64,0	45,6	35,6	26,6	19,0	16,0
5 OPzS 250 LA	102,0	80,0	57,0	44,5	33,0	24,0	20,0
6 OPzS 300 LA	122,0	96,0	68,5	53,5	40,0	30,0	24,0
5 OPzS 350 LA	115,0	93,0	67,5	55,5	42,0	32,5	29,5
6 OPzS 420 LA	133,0	111,0	81,0	66,5	50,5	39,0	35,5
7 OPzS 490 LA	156,0	130,0	94,5	77,5	60,0	45,5	41,5
6 OPzS 600 LA	178,0	158,0	115,0	98,5	75,0	53,5	43,0
8 OPzS 800 LA	238,0	211,0	153,0	131,0	100,0	71,0	57,5
10 OPzS 1000 LA	298,0	264,0	192,0	164,0	125,0	89,0	72,0
12 OPzS 1200 LA	357,0	316,0	230,0	197,0	150,0	107,0	86,5
12 OPzS 1500 LA	345,0	343,0	294,0	261,0	192,0	138,0	110,0
16 OPzS 2000 LA	460,0	460,0	394,0	336,0	258,0	184,0	146,0
20 OPzS 2500 LA	575,0	575,0	493,0	436,0	323,0	230,0	184,0
24 OPzS 3000 LA	690,0	690,0	592,0	523,0	388,0	276,0	220,0

1.87V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	93,0	73,5	51,0	40,0	29,5	21,0	17,5
5 OPzS 250 LA	116,0	92,0	64,0	50,0	36,5	26,0	22,0
6 OPzS 300 LA	139,0	110,0	77,0	60,0	44,0	31,5	26,5
5 OPzS 350 LA	142,0	113,0	82,0	68,0	48,0	36,0	31,0
6 OPzS 420 LA	170,0	135,0	100,0	80,0	57,5	43,5	37,0
7 OPzS 490 LA	200,0	158,0	116,0	94,0	67,0	50,5	43,5
6 OPzS 600 LA	225,0	200,0	140,0	112,0	84,0	60,0	49,0
8 OPzS 800 LA	300,0	244,1	186,0	150,0	112,0	80,0	65,5
10 OPzS 1000 LA	375,0	333,0	235,0	188,0	140,0	100,0	82,0
12 OPzS 1200 LA	450,0	400,0	280,0	225,0	167,0	120,0	98,5
12 OPzS 1500 LA	453,0	427,0	336,0	285,0	212,0	152,0	124,0
16 OPzS 2000 LA	682,0	618,0	465,0	395,0	290,0	204,0	165,0
20 OPzS 2500 LA	853,0	773,0	581,0	493,0	363,0	236,0	208,0
24 OPzS 3000 LA	1023,0	927,0	698,0	592,0	436,0	307,0	249,0

1.83V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	108,0	84,5	57,5	45,0	32,0	23,0	19,0
5 OPzS 250 LA	135,0	105,0	72,0	56,0	40,0	28,5	23,5
6 OPzS 300 LA	162,0	126,0	86,0	67,0	48,0	34,0	28,5
5 OPzS 350 LA	173,0	136,0	98,0	77,0	55,0	39,0	33,0
6 OPzS 420 LA	207,0	163,0	117,0	92,0	66,0	47,0	39,5
7 OPzS 490 LA	242,0	190,0	137,0	108,0	77,0	54,5	46,0
6 OPzS 600 LA	290,0	230,0	174,0	136,0	98,0	69,0	57,0
8 OPzS 800 LA	387,0	307,0	232,0	181,0	131,0	92,0	76,0
10 OPzS 1000 LA	483,0	383,0	290,0	227,0	163,0	115,0	95,0
12 OPzS 1200 LA	580,0	460,0	348,0	272,0	196,0	138,0	114,0
12 OPzS 1500 LA	570,0	504,0	388,0	315,0	234,0	169,0	139,0
16 OPzS 2000 LA	880,0	721,0	546,0	434,0	320,0	225,0	185,0
20 OPzS 2500 LA	1100,0	901,0	683,0	543,0	400,0	282,0	232,0
24 OPzS 3000 LA	1320,0	1082,0	820,0	652,0	480,0	338,0	278,0

1.80V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	120,0	91,0	62,0	48,0	34,0	24,0	20,0
5 OPzS 250 LA	150,0	114,0	77,5	60,0	42,5	30,0	25,0
6 OPzS 300 LA	180,0	137,0	93,0	72,0	51,0	36,0	30,0
5 OPzS 350 LA	193,0	150,0	105,0	83,0	59,0	41,0	35,0
6 OPzS 420 LA	232,0	180,0	127,0	100,0	70,5	49,5	42,0
7 OPzS 490 LA	271,0	210,0	148,0	116,0	82,0	58,0	49,0
6 OPzS 600 LA	322,0	255,0	185,0	146,0	104,0	73,0	60,0
8 OPzS 800 LA	429,0	340,0	247,0	195,0	139,0	97,0	80,0
10 OPzS 1000 LA	537,0	425,0	308,0	243,0	173,0	122,0	100,0
12 OPzS 1200 LA	644,0	510,0	370,0	292,0	208,0	146,0	120,0
12 OPzS 1500 LA	660,0	556,0	422,0	336,0	244,0	179,0	147,0
16 OPzS 2000 LA	970,0	788,0	586,0	460,0	332,0	237,0	196,0
20 OPzS 2500 LA	1213,0	985,0	733,0	575,0	415,0	298,0	246,0
24 OPzS 3000 LA	1456,0	1182,0	880,0	690,0	498,0	357,0	295,0

1.75V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	137,0	100,0	66,0	50,0	35,0	25,0	20,0
5 OPzS 250 LA	172,0	125,0	82,5	63,0	44,0	31,5	25,0
6 OPzS 300 LA	206,0	150,0	99,0	75,0	52,5	38,0	30,0
5 OPzS 350 LA	222,0	168,0	114,0	88,0	61,0	42,0	35,0
6 OPzS 420 LA	266,0	202,0	137,0	106,0	73,0	50,5	42,0
7 OPzS 490 LA	311,0	235,0	150,0	124,0	85,5	59,0	49,0
6 OPzS 600 LA	372,0	290,0	204,0	160,0	112,0	75,0	60,0
8 OPzS 800 LA	496,0	387,0	272,0	213,0	149,0	100,0	80,0
10 OPzS 1000 LA	620,0	483,0	340,0	266,0	187,0	125,0	100,0
12 OPzS 1200 LA	744,0	580,0	408,0	320,0	224,0	150,0	120,0
12 OPzS 1500 LA	768,0	632,0	470,0	366,0	264,0	189,0	147,0
16 OPzS 2000 LA	1120,0	889,0	646,0	498,0	352,0	252,0	196,0
20 OPzS 2500 LA	1400,0	1111,0	808,0	623,0	440,0	316,0	246,0
24 OPzS 3000 LA	1680,0	1334,0	970,0	745,0	528,0	379,0	295,0

1.70V/ogniwo - rozładowanie w A							
Typ	30'	1 h	2 h	3 h	5 h	8 h	10 h
4 OPzS 200 LA	155,0	106,0	69,0	52,0	36,0	24,0	20,0
5 OPzS 250 LA	195,0	133,0	86,5	65,0	45,0	30,0	25,0
6 OPzS 300 LA	232,0	160,0	103,0	78,0	54,0	36,0	30,0
5 OPzS 350 LA	245,0	181,0	121,0	91,0	64,0	41,0	35,0
6 OPzS 420 LA	294,0	218,0	145,0	109,0	76,8	49,5	42,0
7 OPzS 490 LA	343,0	254,0	170,0	128,0	89,6	58,0	49,0
6 OPzS 600 LA	420,0	315,0	215,0	162,0	112,0	73,0	60,0
8 OPzS 800 LA	560,0	420,0	285,0	216,0	149,0	100,0	80,0
10 OPzS 1000 LA	700,0	525,0	358,0	270,0	187,0	122,0	100,0
12 OPzS 1200 LA	840,0	630,0	430,0	324,0	224,0	146,0	120,0
12 OPzS 1500 LA	885,0	695,0	500,0	388,0	268,0	179,0	147,0
16 OPzS 2000 LA	1273,0	1009,0	689,0	530,0	365,0	237,0	196,0
20 OPzS 2500 LA	1591,0	1261,0	861,0	663,0	456,0	298,0	246,0
24 OPzS 3000 LA	1910,0	1514,0	1034,0	796,0	548,0	357,0	295,0

